

#Jenny



Finally I get this ebook, thanks for all these I can get now!

#Rio



Cool! I'am really happy

#Markus Jensen



I did not think that this would work, my best friend showed me this website, and it does! I get my most wanted eBook

#Hun Tsu



wtf this great ebook for free?!

#Che Salsa



My friends are so mad that they do not know how I have all the high quality ebook which they do not!

#Diego Butler



so many fake sites. this is the first one which worked! Many thanks

Field Service Ver.1.0 Nov. 2008 12. JAM CODE

■ TROUBLESHOOTING

12. JAM CODE

12.1 Jam code list

Classification	Jam code	Cause	Resulting operation	Correction
Bypass tray	27000	The registration sensor (PS46) does not turn ON within a specified period of time after the loop motor (M6) turns ON.	If there is a sheet of paper being printed when a jam occurs, the main body completes the paper exit before stopping operations.	Put out the paper from the bypass tray and remove jammed paper if any.
	27002	At the start of the bypass feed, the registration sensor (PS46) turns ON.		
Tray 1	21101	The paper feed sensor (PS1) does not turn ON within a specified period of time after the paper feed clutch (CL3) turns ON.	The paper exit before stopping operations.	Put out the horizontal conveyance section and remove jammed paper if any.
	21102	The horizontal conveyance sensor (R6 (PS6)) does not turn ON with the paper feed sensor (PS1) ON within a specified period of time after the pre-registration clutch (CL4) turns ON.		
	21103	The horizontal conveyance sensor (L1 (PS5)) or the horizontal conveyance sensor (R6 (PS6)) does not turn ON within a specified period of time after the pre-registration clutch (CL4) turns ON.		
	21104	The horizontal conveyance sensor (R6 (PS6)) turns ON while in sliding.		
	21105	The horizontal conveyance sensor (L1 (PS5)) turns ON while in sliding.		
Tray 2	21201	The paper feed sensor (PS1) does not turn ON within a specified period of time after the paper feed clutch (CL5) turns ON.	If there is a sheet of paper being printed when a jam occurs, the main body completes the paper exit before stopping operations.	Put out the tray and remove jammed paper if any.
	21202	The vertical conveyance sensor (PS23) does not turn ON with the paper feed sensor (PS1) ON within a specified period of time after the pre-registration clutch (CL5) turns ON.		
	21203	The vertical conveyance sensor (PS23) does not turn ON with the paper feed sensor (PS1) ON within a specified period of time after the pre-registration clutch (CL5) turns ON.		

[Download PDF version of :](#)
Manual Konica Minolta Bizhub 601 Printer